

OEM Scan Engine

Model	Trigger Command	Return Value	Stop Trigger Command	Return Value
RT211	7E 00 08 01 00 00 D5 EF 41	02 00 00 01 00 33 31	7E 00 08 01 00 02 02 32 b9	02 00 00 01 00 33 31
	7E 00 08 01 00 02 01 02 DA	02 00 00 01 00 33 31		

Find sn

查询esn

7e 00 05 01 01 F0 08 F0 1A

RT211	Serial Port Baud Rate		End suffix
	7E 00 08 01 00 D9 D8 91 53	115200	7E 00 07 01 00 60 01 0A 6B
	02 00 00 01 00 33 31	Return Value	02 00 00 01 A1 96 FA
	7E 00 08 01 00 D9 D3 20 38	9600	
	02 00 00 01 00 33 31	Return Value	7E 00 08 01 00 60 80 EE 3B
	7E 00 09 01 00 00 00 DE C8	Save	02 00 00 01 00 33 31
			7E 00 08 01 00 60 81 FE 1A
	7E 00 07 01 00 2A 02 D8 0F	Find Baud Rate	02 00 00 01 00 33 31
			7E 00 08 01 00 60 A1 DA 78
			02 00 00 01 00 33 31
		7E 00 08 01 00 60 C1 B6 DE	
		02 00 00 01 00 33 31	
		7E 00 09 01 00 00 00 DE C8	

Read Register 0x0060
Return Value 0xA1, Default values

Prohibit the addition of terminator suffixes (0xA1 & (! 0x61) +0x00=0x80)
Return Value

Adding End Suffix CR (0xA1 & (! 0x61) +0x01=0x81)
Return Value

Adding End Suffix CRLF (0xA1 & (! 0x61) +0x21=0xA1)
Return Value

Adding End Suffix TAB (0xA1 & (! 0x61) +0x41=0xC1)

Save

W616000

W616001

W616021

W616041